

PLC device (long)

Command	Data type	Description	PS	AX	RW	Range
M_SSEC_PLLNG_X_1SHOT(x)	T_LONG	Device X (x=0 to 2815 / [M7] x=0 to 8191)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_Y_1SHOT(x)	T_LONG	Device Y (x=0 to 3583 / [M7] x=0 to 8191)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_M_1SHOT(x)	T_LONG	Device M (x=0 to 8191 / [M7] x=0 to 10239)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_F_1SHOT(x)	T_LONG	Device F (x=0 to 255 / [M7] x=0 to 1024)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_L_1SHOT(x)	T_LONG	Device L (x=0 to 255 / [M7] x=0 to 511)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_SM_1SHOT(x)	T_LONG	Device SM (x=0 to 127)(GPPW)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_T_1SHOT(x)	T_LONG	Device T (x=0 to 4255 / [M7] x=0 to 4703)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_C_1SHOT(x)	T_LONG	Device C (x=0 to 4127 / [M7] x=0 to 4255)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_D_1SHOT(x)	T_LONG	Device D (x=0 to 1023 / [M7] x=0 to 2047)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_R_1SHOT(x)	T_LONG	Device R (x=0 to 8191 / [M7] x=0 to 13311)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_E_1SHOT(x)	T_LONG	Device E (x=0 to 127)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_U_1SHOT(x)	T_LONG	Device U (x=0 to 383)(PLC4B)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_W_1SHOT(x)	T_LONG	Device W (x=0 to 511 / [M7] x=0 to 8191) (PLC4B/NET10)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_B_1SHOT(x)	T_LONG	Device B (x=0 to 4103 / [M7] x=0 to 8191) (PLC4B/NET10)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_G_1SHOT(x)	T_LONG	Device G (x=0 to 3071)(PLC4B)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_I_1SHOT(x)	T_LONG	Device I (x=0 to 1023)(PLC4B)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_J_1SHOT(x)	T_LONG	Device J (x=0 to 1599)(PLC4B)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_Q_1SHOT(x)	T_LONG	Device Q (x=0 to 4151)(PLC4B)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_S_1SHOT(x)	T_LONG	Device S (x=0 to 319)(PLC4B)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_SB_1SHOT(x)	T_LONG	Device SB (x=0 to 511) (NET10)	--	--	RW	0x00000000 to 0xFFFFFFFF

M_SSEC_PLLNG_V_1SHOT(x)	T_LONG	Device V (x=0 to 255) (NET10)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_SW_1SHOT(x)	T_LONG	Device SW (x=0 to 511) (NET10)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_SD_1SHOT(x)	T_LONG	Device SD (x=0 to 127) (NET10)	--	--	RW	0x00000000 to 0xFFFFFFFF
M_SSEC_PLLNG_ST_1SHOT(x)	T_LONG	Device ST (x=0 to 4063)(M7 GPPW)	--	--	RW	0x00000000 to 0xFFFFFFFF